

# ALCATEL 4200

*Easy*

---

*Courtesy of DownerCommspec (NZ) Ltd*



For Sales and Service

**DownerCommspec (NZ) Ltd**

**0800-828-888**



## MAKING CALLS

<b>OUTWARD DIALING</b>	Dial 1, followed by the desired number
<b>INTER OFFICE CALLING</b>	Dial extension number
<b>CALLBACK</b> <i>If an extension is engaged you may programme your phone to ring you when the extension is free</i>	After you have dialled the extension and hear busy tone  Dial 5 to set a Callback  To Cancel dial # 99
<b>REDIAL</b>	Dial # 1



## DIRECTORY DIALING

<b>BY NUMBER</b>  <i>Accesses up to 400 Company speed dials by number</i>	Dial the 4 digit speed code 8000 - 8399
<b>BY NAME</b>  <i>Dials Internal and Company names using Directory</i>	<ol style="list-style-type: none"> <li>1. Press DIRECTORY key</li> <li>2. From your alpha keypad, enter the first letter of the name you require</li> <li>3. Press + or - to scroll to desired name</li> <li>4. Press OK the number is automatically dialled for you</li> </ol>

## PERSONAL SPEED DIALING

<b>PROGRAMMING</b>  <i>Stores and accesses up to 10 speed dials exclusive to your phone</i>	<ol style="list-style-type: none"> <li>1. Press PERSONAL SPEED key</li> <li>2. Press </li> <li>3. Enter a speed number between 1 - 9</li> <li>4. Enter the name from your alpha keypad</li> <li>5. Press OK</li> <li>6. Dial 1 followed by the telephone number</li> <li>7. Press OK </li> </ol>										
	<table border="1" style="width: 100%;"> <tr> <td style="width: 50%;">0</td> <td style="width: 50%;">1</td> </tr> <tr> <td>2</td> <td>3</td> </tr> <tr> <td>4</td> <td>5</td> </tr> <tr> <td>6</td> <td>7</td> </tr> <tr> <td>8</td> <td>9</td> </tr> </table>	0	1	2	3	4	5	6	7	8	9
0	1										
2	3										
4	5										
6	7										
8	9										
<b>TO DIAL</b>	<ol style="list-style-type: none"> <li>1. Press PERSONAL SPEED key</li> <li>2. Press + or - to scroll to desired name</li> <li>3. Press OK The number is automatically dialled for you</li> </ol>										

## FEATURE CODES

1	Outside Line
0	Operator
8000 - 8399	Dialling a System Directory number
5	Automatic Call back
# 99	Cancel automatic callback
# *	Paging All Calls
# 2	Paging Group
* 7	Parking a Call
* 7	Retrieve Parked Call from your extension
* 7 (extn)	Retrieve Parked Call from your own or another extension
# 6 (extn)	Direct Pick Up
* 6	Group Pick Up
* 1	Bell Pick Up
* 01	Forward All Calls
* 02	Forward Calls on Busy
* 00	Cancel Call Forwarding
* 06	Forward I'm Here
* 07	Cancel Forward I'm Here
# 1	Redial
3	Conference
 552	Headset ON
 551	Headset OFF

## INFORMATION KEY



Press

Press + or - to scroll and select from the following additional features

Each time the desired feature is displayed on your screen, press the OK key to confirm your choice

## FEATURES

1. **WHO AM I** – Displays your extension number
2. **LOCK** – Disables your phone from being used
3. **APPMT** – (Appointment) By inserting a time (4 digits) you may get your phone to ring you (Alarm)
4. **DIVERT** – Diverts your phone or enables text messaging
5. **PHONE** – Enables Headset use, Contrast (Dial 1), Melody (Dial 1 for tune and Dial 2 for Volume)

## SENDING DTMF TONES

**FOR AUTOMATED  
TELEPHONE  
MESSAGING, e.g.  
TELEPHONE BANKING;  
VOICEMAIL ETC**

Dial the required number  
Press DTMF key or Dial # #  
Dial the required digits from your keypad

## RECEIVING CALLS

**GROUP PICK UP**  
*Answers any ringing phone in your group*

Press PICKUP or Dial \* 6

**DIRECTED PICK UP**  
*Answers a specific ringing phone*

Press DIR PICK or Dial # 6  
Dial the extension number you wish to answer

**ANSWERING NIGHT BELLS**

Dial \* 1

## TRANSFERRING

**TRANSFER**

Ask your caller to hold  
Dial extension number  
Wait for an answer (optional)  
Press TRANSFER and hang up

➤ **To Retrieve the call if you have not hung up**

Press then CALL key (flashing)  
You are connected to your caller

➤ **To Retrieve the call if you have hung up**

Press DIR PICK or Dial # 6  
Followed by the extension number

## CALL WAITING

**IGNORE THE CALL**

It will return to its sender

**REPLACE YOUR RECEIVER**

The 2<sup>nd</sup> call will ring your phone

**ANSWER THE CALL WAITING AND HOLD YOUR 1<sup>ST</sup> CALLER**

Ask your caller to hold  
Press flashing CALL key (first caller goes on hold automatically)  
You are connected to the 2<sup>nd</sup> caller

**SHUTTLE BETWEEN THE TWO CALLERS**

Press CALL key (flashing) to shuttle between the two callers

## HOLDING

**HOLD A CALLER**

Ask your caller to hold  
Press HOLD key

**RETRIEVE CALL ON HOLD**

Press CALL key (flashing)

<b>PARKING</b>	
<b>PARK</b>	Ask your caller to hold Press PARK (or Dial * 7)
<b>PARK RETRIEVE</b>	Press PARK (or Dial * 7) Dial the extension number the call is parked at
<b>PAGING</b>	
<b>ANSWERING PAGE</b>	From any phone Dial * 7 followed by the number announced by the operator
<b>ALL CALLS</b>	Dial # *
<b>PAGING GROUP</b>	Dial # 2
<b>CONFERENCING</b>	
<b>CONFERENCING UP TO 3 PARTIES</b> <i>Any combination internal and external</i>	While in conversation Dial the extension you wish to conference (Speak with the new party – the other party can not hear) Press 3 to conference all parties
<b>LEAVING A TEXT MESSAGE FROM YOUR PHONE</b>	
<b>TO SET</b> <i>Displays a visual message to screen phone extensions</i>	<ol style="list-style-type: none"> <li>1. Press <b>[1]</b></li> <li>2. Press + (until 4-Div is displayed on screen)</li> <li>3. Press OK</li> <li>4. Press + (until Text is displayed on screen)</li> <li>5. Press OK</li> <li>6. Press + and - (until desired message is displayed on screen) Enter information from your keypad where prompted, press OK</li> <li>7. Press OK "Text Answering" is now displayed on your screen</li> </ol> <p>To Cancel Dial * 00 or Press DIVERT</p>

<b>SENDING A TEXT MESSAGE</b>	
<b>TO SET</b> <i>Sends a visual text message to Display phones</i>  <i>(N.B. Once sent the message can not be cancelled)</i>	<ol style="list-style-type: none"> <li>1. Press MAIL key</li> <li>2. Dial 2</li> <li>3. Enter destination extension</li> <li>4. Press + and - (until desired message is displayed on screen)</li> <li>5. Press OK Pressing NEXT SCREEN will view second part of longer messages</li> <li>6. Press OK</li> </ol>
<b>READING A TEXT MESSAGE</b>	
<b>WHEN YOUR MAIL KEY IS ILLUMINATED</b>  <i>(Feature only available if your phone is programmed with a NEXT SCREEN key)</i>	<ol style="list-style-type: none"> <li>1. Press MAIL key (Screen displays how many text or voice messages received)</li> <li>2. Press 2 (Senders name is displayed on screen)</li> <li>3. Press OK Press NEXT SCREEN to read message</li> <li>4. Press OK (Calls sender and deletes message)</li> </ol>
<b>DIVERTING CALLS</b>	
<b>TO SET</b>	<ol style="list-style-type: none"> <li>1. Press <b>[1]</b></li> <li>2. Press + (until 4-Div is displayed on screen)</li> <li>3. Press OK</li> <li>4. Press + (until desired Divert type is displayed on screen)</li> <li>5. Press OK</li> <li>6. Enter destination extension</li> </ol> <p>To Cancel Dial * 00 or Press DIVERT</p>