

# Alcatel 4200 Advanced Handset User Guide





Making / Receiving Calls

To make an Internal call Press the relevant **Extension Key** or dial the **Extension Number** 

To make an External call Dial 9 or press the Line Key and then the Telephone Number

To answer a call Lift the handset or press to answer in handsfree

Transferring / Holding Calls

To hold a call Press **Hold** 

To retrieve a held call Press the line key with the **Music Symbol** next to it

To transfer a call Call the **Extension Number** and then press transfer

To cancel transfer Press then the line key with the Music Symbol next to it

Handling Several Calls

To transfer to external source While on the 1st call dial the 2nd telephone number or extension number, this will put the

1st call on hold. Transfer or retrieve the 1st call as normal

To shuttle between 2 calls

Press the relevant Line Key. This will automatically put your original call on hold and

answer the second

Speed Dials

To dial by name

Type in the letters of the name you require. Press **Next** or **Previous** to scroll. Press

Send to call the number

To dial by Short Code Dial the Short Code Number (please see your list).

System Features

To use Touch Tones Press **DTMF** before you choose your first option

To activate Call Back Dial the Extension Number and press Cback

To cancel Call Back Dial #

Redial Press **Redial** use **Prev** and **Next** to scroll through the last ten numbers dialled.

To temporary store a dialled Press **NBsave** before hanging up.

number To call this number again press **StoreN**.

To set a temporary Appointment Press **Appmnt** and type in the required time, press **OK** 

To cancel a set Appointment Press **Appmnt**, press **Clear** and then press **OK** 

To have a conference call

During your call dial the person you wish to include and when they answer press Conf

key or dial 50

To Broadcast to other phones Dial 41 and speak into handset

Group pick up Dial 14 or press Pick-up key

Individual pick-up Dial 13 and the relevant Extension Number

To park a call

(Store a call on an extension)

Dial 12

To retrieve a parked call Dial 12 and then the Extension Number that the call was parked on

#### **Diverts**

To Divert Internal and External Calls Dial 61 and the Extension Number you wish to divert to

To Divert on Busy Dial 62 and the Extension Number you wish to divert to

To set a DND (Do Not Disturb) Dial 63

To cancel all Diversions Dial 60

#### **Attendant Diversion**

Note that an Attendant Diversion will need to be configured by G B Telecom

To divert Incoming Calls Press **Divert** and press the **Password Key** 

To cancel Attendant Diversion Press **Divert** and press the **Password Key** 

## Personal Speed Dials

Note that a Speed key will need to be configured by G B Telecom

To program Personal Speed Press **Speed**, Press **i** 

Dials Select soft key where you wish to store the number (Soft keys are under the screen)

Insert the name using the keypad

Press **OK** 

Insert the external telephone number (prefixed by a 9)

Press OK

To call a Personal Speed Dial Press Speed

Press the relevant soft key

#### **Text Messaging**

Receiving a text message/ Press Mail or Envelope key

Unanswered Call Press Text
Press Read

Press MSG

Press **Call** to call them back Press **Clear** to delete the message

Press Exit

To send a Text Message Press Mail or Envelope key

Press Text and enter the destination Extension Number Scroll by pressing Next to view

pre-typed message

Press **OK** to send the message

# Changing Ring Tones / Contrast

Change your Ring Tone/Volume Press Phone Press Melody

Press **Tune** + repeatedly for choice of melody Press **Level** + repeatedly for choice of volume

Press **OK** to select Press **Back** and then **Exit** 

To change screen Contrast

Press Press

Press **Phone**Press **Contrast** 

Press Screen + repeatedly to amend the screen contrast

Press Icon + repeatedly to amend the

icon contrast Press **OK** to select Press **Back** then **Exit** 

# To Activate your Headset

Press Phone
Press Headset

Press **Choice** to switch headset On/Off Press **OK** to confirm your choice

## Voicemail

Press 🕮 To initialise your mailbox

Press 3

Enter a 4 digit personal password

(default 2222) Say your name Press #

Press 📟 To record your greeting Press 3

Enter your 4 digit personal password Press 4 for Personal Options Press 1 to Change Greeting Press 4 to Record Greeting Press # to Confirm

Press 🕮 To record your name only Press 3

> Enter your 4 digit personal password Press 4 for Personal Options Press 5 for To Record Your Name

Press # to Confirm

Accessing your message Press the Mail or Envelope Key

Press 3

Enter your password - 2222 (default password)

Press 1 to Listen to your message

Press 2 to Archive

Press 3 to erase your message

Accessing your message from Dial your DDI number

Out with the office When your message begins press \* then #

on your telephone

Enter your mailbox number Enter your personal password Press 1 to listen to your message Press 2 to archive the message

Press 3 to erase

To activate your Voicemail Dial 61 and then 51

To take your Voicemail off Dial 60

# Night Services

Note that Night Service will need to be configured by G B Telecom

To Activate your Night Service Press NR Mode

Press Password

Dial 61 and then 51 or press Vmail On

Press NR Mode To take your Night Service off

Press Password

Dial 60 or press Vmail off

Notes	

# G B Telecom (Scotland) Ltd Contacts

General Enquiries

Galamoor House Netherdale Galashiels TD1 3EY

Telephone 01896 752607 Fax 01896 661308

E-mail <u>enquiries@gbtelecom.co.uk</u>

Sales

Telephone 01896 661313

E-mail <u>sales@gbtelecom.co.uk</u>

Faults, Technical and Training

Telephone 01896 661319

E-mail <u>support@gbtelecom.co.uk</u>

Network

Telephone 01896 661317

E-mail <u>network@gbtelecom.co.uk</u>

Accounts

Telephone 01896 661303

E-mail <u>accounts@gbtelecom.co.uk</u>